

SKU: 165 ES20F-200/2

Phase Single RPM 3000 Voltage Outputs 115/230 With AVR

Mecc Alte ES Series are single phase, 3000 rpm, AVR controlled, brush generators. Power range is from 4.5kVA to 11kVA. Fitted with an Automatic Voltage Regulator (AVR), Manufactured in Italy

This unit is designed to be fitted to an engine with a taper shaft (j609b coupling). Check the attached technical drawing to match against your existing coupling. If a different coupling is required, please contact us for availability.

This alternator can also be run via a belt a pulley with a bearing kit.

Suitable engines include Honda GX630, GX690, Kohler KD425

SPECS:

- Phase: Single
- RPM: 3000
- Voltage Outputs: 115/230
- Frequency: 50Hz
- Rated Output (kVA): 11
- Power Factor: 1
- Rated Output (kW): 11
- Taper Fitting: J609b
- Through Bolt Length: TBC
- THD: <4%

